Metz CUBUS

Inspirational technology for pure TV enjoyment.







































Qualcomm^{*}

The CUBUS promises a remarkably sharp viewing experience thanks to its direct LED display in HD resolution and 400 MetzVision technology. Local area dimming optimises the contrast and helps make the television more energy efficient. A twin multi-tuner and two CI+ interfaces equip it to receive free and pay TV via all available reception modes. A sealed 2-way system and bass reflex channel mean MetzSoundPro technology will deliver crystal clear trebles and rich bass frequencies that bring sound to life through six front-facing speakers. WiFi, Bluetooth® and an extensive range of interfaces make it a truly versatile all-rounder. Thanks to its comprehensive USB recording function, this TV reaches its full potential when an external data medium with timeshift and recording functions is connected to it.



A beautifully shaped, rotating black glass stand gives it a stable base.



Graphite grey acoustic fleece with brilliant black brushed aluminium trim and surround.



The clear RM18 remote control in black is matched by the clearly arranged menu.



With the MetzRemote app can be using controlled conveniently smartphone or a tablet.



Metz CUBUS



	Cubus 50	Cubus 43
Product data sheet	TY66 UHD twin	TY66 UHD twin
Picture technology		
Display technology (local dimming zones)	LCD /Direct-LED (4x4)	LCD / Direct-LED (4x4)
Aspect ratio	16:9 3840x2160 (10 Bit) UHD	16:9 3840x2160 (10 Bit) UHD
Resolution [px hor x px vert] Diagonal screen size [cm / inch]	126 / 50	108 / 43
Visible screen area [dm²]	67,5	49,8
HDR10/HLG/Technicolor®/HDR10+™/Dolby Vision™	•/•/-/-	•/•/-/-
Picture technology index	400 MetzVision	400 MetzVision
Max. contrast ratio / Panel brightness max. [cd/m²]	700.000 : 1 / 600	700.000 : 1 / 500
Automatic brightness control ABC / HD-PIP	•/• 178° / 9,5	•/• 178°/5
Viewing angle type (typical) / Typical response time in ms (GTG) Sound technology	1/0 / 7,3	176 73
Music output power [W]	2 × 20	2 × 20
Integrated speakers / Subwoofer / 7-Band Equalizer	6/-/•	6/-/•
Dolby Digital Plus / HE-AAC	•/•	•/•
Audio output Line / variable Audio-mode	MetzSoundPro	MetzSoundPro
Separate headphone volume adjustment	•	•
Automatic volume control (can be disabled)	•	•
Bluetooth® retrofittable	•	•
Operation	Diviso (División de la companya della companya della companya de la companya de la companya della compan
Remote Control / Direct control of external streaming devices	RM18 / •	RM18 / •
Harddisk recorder incl. Timeshift USB recording / USB Timeshift	- •/•	- •/•
Power switch / Status-Display	• / LED	•/LED
Sleeptimer / Picture freeze / Child lock	•/•/•	•/•/•
Electronic programme guide (EPG) / Internet-Timer	•/•	•/•
Top teletext / TT-comfort functions / Tri-star menu incl. Hotelmode	●/●/●	●/●/●
Reception Equipped with tuner ex works	2 x DVB-C/T2/S2	2 x DVB-C/T2/S2
HDTV / UHDTV integrated	•/•	•/•
HEVC (H.265) / Number of CI+ compatible CI slots	•/2	•/2
Smart-TV (Media- / Network functions)		
Operating system	Linux	Linux
Streaming (Server / Client)	• (•/•)	• (•/•)
LAN / \\ \ AN / \EE902.11 a/b/a/a/a a. 2.4 CHz + E.0 CHz\	-/-	
LAN / WLAN (IEE802.11 a/b/g/n/ac; 2,4 GHz + 5,0 GHz) Metz Remote App / Smart TV Portal	•/• • / Foxxum	· ·
LAN / WLAN (IEE802.11 a/b/g/n/ac; 2,4 GHz + 5,0 GHz) Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5	•/• • / Foxxum •/•/•	• / Foxxum •/•/•
Metz Remote App / Smart TV Portal	• / Foxxum	• / Foxxum
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC	• / Foxxum •/•/•	•/Foxxum •/•/• 3/3/1
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0	•/Foxxum •/•/• 3/3/1 1/1	•/Foxxum •/•/• 3/3/1 1/1
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/•	•/Foxxum •/•/• 3/3/1 1/1 •/•
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog	•/Foxxum •/•/• 3/3/1 1/1	•/Foxxum •/•/• 3/3/1 1/1
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/•	• / Foxxum •/•/• 3/3/1 1/1 •/• •/•
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter)	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/•	• / Foxxum •/•/• 3/3/1 1/1 •/• •/•
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized)	• / Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/ • 230-240V~ 50Hz internal	• / Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/230-240V~ 50Hz internal
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W]	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/ •/ 230-240V~ 50Hz internal 78,0	• / Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/230-240V~ 50Hz internal 60,0
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR)	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• •/• •/• •/• 230-240V~ 50Hz internal 78,0 G	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 1 / 1 •/• •/• •/• •/230-240V~ 50Hz internal 60,0 G
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W]	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/ •/ 230-240V~ 50Hz internal 78,0	• / Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/230-240V~ 50Hz internal 60,0
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR)	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• •/• 230-240V~ 50Hz internal 78,0 G 148,0	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• •/ 230-240V~ 50Hz internal 60,0 G 115,0
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W]	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• •/• 230-240V~ 50Hz internal 60,0 G 115,0 G
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W]	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm]	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm] Height with base / without base [cm]	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00 112,0 74,2/71,5	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00 96,4 65,3 / 62,8
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm] Height with base / without base [cm] Weight with base / without base [kg] Width x Depth base [cm]	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00 112,0 74,2/71,5 30,0/8,3 19,9/16,6 49,0 x 30,0	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00 96,4 65,3 / 62,8 30,0 / 8,3 16,7 / 13,4 49,0 x 30,0
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm] Height with base / without base [cm] Weight with base / without base [cm] Weight with base / without base [kg] Width x Depth base [cm]	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• •/• 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00 112,0 74,2/71,5 30,0/8,3 19,9/16,6	• / Foxxum • /•/• 3 / 3 / 1 1 / 1 • /• • /• • /• 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00 96,4 65,3 / 62,8 30,0 / 8,3 16,7 / 13,4
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm] Height with base / without base [cm] Depth with base / without base [cm] Weight with base / without base [kg] Width x Depth base [cm] Wallmount width x height [cm] (VESA) Other information	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00 112,0 74,2/71,5 30,0/8,3 19,9/16,6 49,0 x 30,0 20 x 20	• / Foxxum •/•/• 3 / 3 / 1 1 / 1 •/• •/• •/• •/• • 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00 96,4 65,3 / 62,8 30,0 / 8,3 16,7 / 13,4 49,0 x 30,0 20 x 20
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm] Height with base / without base [cm] Depth with base / without base [cm] Weight with base / without base [kg] Width x Depth base [cm] Wallmount width x height [cm] (VESA) Other information EAN	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00 112,0 74,2/71,5 30,0/8,3 19,9/16,6 49,0 x 30,0 20 x 20 40 57313 011373	• / Foxxum • /•/• 3 / 3 / 1 1 / 1 • /• • /• • /• • 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00 96,4 65,3 / 62,8 30,0 / 8,3 16,7 / 13,4 49,0 x 30,0 20 x 20 40 57313 011380
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in fi mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm] Height with base / without base [cm] Depth with base / without base [cm] Weight with base / without base [kg] Width x Depth base [cm] Wallmount width x height [cm] (VESA) Other information	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00 112,0 74,2/71,5 30,0/8,3 19,9/16,6 49,0 x 30,0 20 x 20	• / Foxxum • /•/• 3 / 3 / 1 1 / 1 • /• • /• • /• 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00 96,4 65,3 / 62,8 30,0 / 8,3 16,7 / 13,4 49,0 x 30,0 20 x 20
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in fi mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm] Height with base / without base [cm] Depth with base / without base [cm] Weight with base / without base [kg] Width x Depth base [cm] Wallmount width x height [cm] (VESA) Other information EAN Mercury content [mg]	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00 112,0 74,2/71,5 30,0/8,3 19,9/16,6 49,0 x 30,0 20 x 20 40 57313 011373 0,0	● / Foxxum ● /● /● 3 / 3 / 1 1 / 1 ● /● ● /● ● 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00 96,4 65,3 / 62,8 30,0 / 8,3 16,7 / 13,4 49,0 × 30,0 20 × 20 40 57313 011380 0,0
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm] Height with base / without base [cm] Depth with base / without base [cm] Weight with base / without base [kg] Width x Depth base [cm] Wallmount width x height [cm] (VESA) Other information EAN Mercury content [mg] Device contains lead (within prescribed legal limits) Guaranteed software and firmware updates until Guaranteed availability of spare parts	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00 112,0 74,2/71,5 30,0/8,3 19,9/16,6 49,0 x 30,0 20 x 20 40 57313 011373 0,0 •	● / Foxxum ● /● /● 3 / 3 / 1 1 / 1 ● /● ● /● ● 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00 96,4 65,3 / 62,8 30,0 / 8,3 16,7 / 13,4 49,0 x 30,0 20 x 20 40 57313 011380 0,0 ●
Metz Remote App / Smart TV Portal Internet radio (preinstalled) / Browser / HbbTV 1.5 Connectivity HDMI input with HDCP 2.2 (4K60/50p 4:4:4) / incl. CEC / and with ARC USB 2.0 / USB 3.0 LAN network connection (RJ 45) / Headphone socket S/PDIF digital audio output - optical / Audio output analog Audio Video in (Cinch via adapter) Power consumption / Energy-efficiency Mains voltage Power supply (power supply unit internal, external, standardized) Power consumption on mode (SDR) (in delivery condition) [W] Energy efficiency class on-mode (SDR) Power consumption in use HDR [W] Energy efficiency class HDR Power consumption in networked standby mode [W] Power consumption in standby mode [W] Power consumption in off mode [W] Dimensions / Weight Width [cm] Height with base / without base [cm] Weight with base / without base [cm] Weight with base / without base [kg] Width x Depth base [cm] Wallmount width x height [cm] (VESA) Other information EAN Mercury content [mg] Device contains lead (within prescribed legal limits) Guaranteed software and firmware updates until	•/Foxxum •/•/• 3/3/1 1/1 •/• •/• •/• •/• •/• •/• •/• • 230-240V~ 50Hz internal 78,0 G 148,0 G 1,20 0,15 0,00 112,0 74,2/71,5 30,0/8,3 19,9/16,6 49,0 x 30,0 20 x 20 40 57313 011373 0,0 • 8 Years	● / Foxxum ● /● /● 3 / 3 / 1 1 / 1 ● /● ● /● ● 230-240V~ 50Hz internal 60,0 G 115,0 G 1,20 0,15 0,00 96,4 65,3 / 62,8 30,0 / 8,3 16,7 / 13,4 49,0 x 30,0 20 x 20 ■ 8 Years